

# EX2000 SERIES MULTI-VEND STATION



## Size and weight

- Height: 27.25"
- Width: 13"
- Depth: 5.5"
- Weight: 45-55 lbs

## Power

- 24VAC

## Display

- 2x16 backlit LCD
- Alphanumeric
- Editable text on screen

## External controls

- 10 digit numeric keypad
- Forward, Backward, Enter, Eject
- Coin return
- 2-bypass keys

## Sensors

- Use exact change (when coin-tubes are low)
- Minimum copy vend (requires a "vended" copy before making change)
- Auto detect coin count

## Copy system requirements

- Copier interface: H20-"Copier OEM"
- Smart interface required on select-models

## Print system requirements

- Compatible with multiple pay-for-print software solutions
- Print Release Station configuration

## Environments

- University Library
- Public Library
- Court House
- Grocery Store
- Convenience Store
- Copy Shop

## Languages

- Supports English

## Processor

- EXTechnology control board
- Multiple prices: choose between b/w, color, and premium paper sizes (on most copier models)
- Field programmable (copier models selected via external keypad)

## In the Box

- EX2000 Series coin-op
- H20-Copier OEM (copy harness)
- Stand (optional)
- Power Supply
- 3 sets of keys (door, cashbox, bypass)
- Owner's manual

## Assembly & Warranty

- Made in USA
- Standard 1 Year Warranty
- Extended Warranty (optional)

## Configuration Options

- EX2000: coins only
- EX2000B: coins & bills
- EX2000CCB: coins, bills, credit cards
- Apple Pay, Android Pay

## Stands & Accessories

- 7000EFS: standard base
- ACDL-114: paper drawer lock

## Capacities

- Nickels: 86, Dimes: 125, Quarters: 95
- Cashbox: approximately \$500 in change
- 100 User codes

## Internal Components

- Coinco 3-tube changer
- (Optional) Coinco 4 or 6-tube changer
- Coinco bill stacker: \$1's, \$5's, \$10's & \$20's
- Euro Coinco 3-tube changer and bill stacker

**ACDI**  
**HARDWARE**  
Card Readers / Payment Solutions

[acd-inc.com/paymentsolutions](http://acd-inc.com/paymentsolutions)